


Dromex



PU2001B GLOVE

EN 388:2003



4131



PU2001B

Description

Dromex® PU2001B black PU (Polyurethane) coated nylon gloves designed with high dexterity, comfort and durability. Provides protection against abrasion. Suitable for applications such as packaging, inspection and fine component assembly in electronic, computer and automotive and small parts handling requirements.

The nylon liner in combination with black polyurethane coating provides superior dexterity and sensitivity, with a breathable back for comfort.

Special Instructions

Although the manufacturer has examined these gloves under the system for ensuring quality of production by means of monitoring and inspection, we recommend that all gloves should be thoroughly inspected before use to ensure no damage is present.

None of the materials or processes used in the manufacture of these products are known to be harmful to the wearer. The gloves and information contained herein are designed to accommodate the basic safety requirements and standards for Personal Protective Equipment. Actual conditions of use cannot be directly simulated in a test environment, so it is therefore the responsibility of the user and not the manufacturer or supplier to determine the suitability for intended use.

Compliance & Conformity

Complies with the requirements of CE type examinations EN420 for innocuousness and EN 388 for compliance with directive 89/686/EEC Mechanical Risks (4,1,3,1). Quality System conforms to ISO9001:2008.

Specifications

Style:	PU (Polyurethane) dipped palm and fingers
Liner:	Nylon
Palm:	PU coated 0.85mm ± 5 %
Back:	Nylon 0.8 mm ± 5 %
Cuff:	Elasticated nylon
Mass:	± 26 g per pair (size 10)

Sizes Available

7-10

Packaging, Storage & Obsolescence

Packed in individual polybags and sold as 240 pairs in a carton. Store in a cool dry place and out of direct sunlight and UV light. Stored correctly, the gloves physical properties will not change for up to three years.



Cleaning & Maintenance

Gloves should not be left in a contaminated condition if re-use is intended especially if potential hazards exist. Before removal from the hands excess contaminant should first be removed from the gloves. Should this not be possible, it is advisable to ease left and right hand gloves off, using the gloved hand and remove the gloves without the contaminant contacting the bare hands. The gloves may then be de-contaminated with a mild detergent solution then rinsed with clean water and air dried.

Disposal

All industrial waste should be disposed of correctly according to local regulations and good disposal practice. Gloves should be disposed of considering the hazardous substances they were used for. Please consider recycling.

Materials



1. Winged thumb
2. PU coated palm & fingers
3. Knitted wrist

Marking

