

Dromex



RE-USEABLE EAR PLUGS
EG-3301B



EG-3301B

Description

The Dromex® EG-3301B, high visibility soft pliable, under the chin thermoplastic rubber ear plugs is designed with optimum protection and comfort of the ear canal offering the highest level of protection against noise.

These easy to insert, lightweight, non-toxic, non-irritating waterproof, are washable, reusable and easy to carry. The EG-3301B is comfortable for long-term wear in hot, humid work areas. Individually packed for hygienic dispensing even when installed in dusty production areas.

Suitable for use in environments such as machining, grinding, steel cutting and woodwork.

Special Instructions

- Do not share ear plugs as ears can be exposed to ear infections.
- The ear plugs should be worn properly at all times in noisy surroundings.
- The ear plugs should be fitted, adjusted and maintained in accordance with instructions provided in the packaging.
- If the recommendations are not adhered to, the protection afforded by the product will be severely impaired.
- The ear plugs may be adversely affected by certain chemical substances; avoid the use of agents (i.e. solvents and other disinfectants) that are known to be harmful to the wearer and/or the ear plug.
- Regularly inspect for tears or cracks and replace if service ability is suspected to be affected. Banded ear plugs should not be used where there is a risk that the connecting band could be caught up during use.
- Sounds above 85dB are harmful to the ears.

Compliance & Conformity

Manufactured to EN 352-2: 2002 as per the requirements of EC Type – examination certificate Directive 89/686/EEC by BSI.

Specifications

Style:	Under the chin preformed triple flange re-usable ear plugs with band.
Material ear plug:	Thermo plastic rubber.
Material band:	Polyacetal resin.
Noise attenuation data:	SNR 28 dB H 28 dB M 25 dB L 25 dB.

Packaging, Storage & Obsolescence

- Packed in pairs in an easy-open polybag. Sold as 20 in a packet and 400 units in a carton.
- Users instructions are included in the packaging.
- Clean and dry ear plugs after use and when not used for a long period of time.
- Store ear plugs in its original packing or suitable container when transporting and not in use.
- Keep away from mechanical and chemical hazards.

Cleaning & Maintenance

After each use wash and rinse with warm mild soapy water.
Dry naturally.


Shelf life

Recommended shelf life of this ear plug is 3 years if un-used and stored in protective packaging. Discard if noticeable damages such as tears appears on the ear plug.

Materials

None of the materials used in the manufacture of these products are known to adversely affect the hygiene or health.

Fitting your Reusable Ear Plugs



1

Position the band under your chin, slightly pull it apart before inserting the ear plugs into the ear canals.



2

Pull up the outer ear and make the ear play stay properly.



3

Gently press the ear plugs inward to achieve effective seal.

Disposal

All industrial waste should be disposed of correctly as per local regulations and good disposal practice. Hearing protective devices should be disposed of considering the hazardous substances they were used for. Please consider recycling.